



- 1 -

## TITLE OF THE INVENTION

METHOD OF GENERATING ASIC DESIGN DATABASE

## BACKGROUND OF THE INVENTION

5 The present invention relates to a method of generating an ASIC design database, which is important when a large-scale integrated circuit device such as a system LSI is to be designed.

10 There is known a conventional design method, which uses a database in order to avoid useless repetition at the time of re-designing or disability of design, when a system LSI is to be developed.

15 In designing an ASIC (Application Specific Integrated Circuit), a designer first analyzes given design specifications, examines architecture candidates, selects a most prospective architecture, and describes the selected architecture using a hardware description language. The act of the describing is called "operation description". The obtained operation description is an operation-level  
20 design result. The operation-level design is verified by applying an operation-level simulator or a verifier to this operation-level design result.

25 Based on the operation description, the designer then produces an RTL (Register Transfer Level) description in which the object of design is described in a register transfer level. The RTL description is automatically generated from the operation description

by means of an operation synthesis tool. The generated  
RTL description is also based on a hardware description  
language (HDL). The RT level design is verified by  
applying an RT level simulation tool, etc. to the RTL  
description.

Following the verification, a net list (gate-level  
logic circuit description), in which the object of  
design is described in a gate level on the basis of the  
RTL description, is generated by means of a logic  
synthesis tool. The gate-level design is verified by  
applying a logic simulation tool, etc. to the net list,  
following which a floor plan is carried out. In the  
floor plan for the net list, blocks constituting gate-  
level logic circuits are generally arranged and wired.

Subsequently, based on the result of the floor  
plan, the gate-level design represented by the net list  
is evaluated. Specifically, using the information on  
the arrangement of blocks constituting logic circuits  
and the information on the wiring of the blocks, the  
layout area, timing, power consumption, etc. are  
calculated.

In general, when the data mentioned above is  
stored, it is divided into specification data and RTL  
description data.

The specification data contains data on the  
process time, layout area, power consumption, test  
cost, etc.

The RTL description data is an RTL description file in units of an entity.

In the methods of constituting the databases, it is necessary to perform a process for extracting the content of specifications after the design is finished. This results in useless procedures in constituting the database.

#### BRIEF SUMMARY OF THE INVENTION

The object of the present invention is to provide a method of generating an ASIC design database, the method being capable of generating a database necessary for re-use design and efficient information collection, which are necessary when a large-scale integrated circuit device such as a system LSI is to be designed.

In order to achieve the object, the present invention may provide a method of generating an ASIC design database, comprising: extracting, when a function design using description data comprising a header portion and an entity portion has been performed, information necessary for reuse design from various execution results of the entity portion; writing the extracted information necessary for reuse design in the header portion of the description data; and storing, as one file at a predetermined location, the description data comprising the header portion in which the information necessary for reuse is written, and the entity portion.

Additional objects and advantages of the invention will be set forth in the description which follows, and in part will be obvious from the description, or may be learned by practice of the invention. The objects and advantages of the invention may be realized and obtained by means of the instrumentalities and combinations particularly pointed out hereinafter.

#### BRIEF DESCRIPTION OF THE SEVERAL VIEWS OF THE DRAWING

The accompanying drawings, which are incorporated in and constitute a part of the specification, illustrate presently preferred embodiments of the invention, and together with the general description given above and the detailed description of the preferred embodiments given below, serve to explain the principles of the invention.

FIG. 1 is a block diagram schematically showing the structure of an IC design support apparatus according to the present invention;

FIG. 2 is a flow chart illustrating the generation of a database and operations for collecting information;

FIG. 3 shows an example of a function design using RTL description;

FIG. 4 shows an example of a simulation result;

FIG. 5 shows an example of an analysis support (area information);

FIG. 6 shows an example of an analysis report

(timing information); and

FIG. 7 shows an example of a power consumption calculation result.

#### DETAILED DESCRIPTION OF THE INVENTION

5           An embodiment of the present invention will now be described with reference to the accompanying drawings.

10           FIG. 1 schematically shows the structure of an integrated circuit design support apparatus according to an ASIC design database generating method of the present invention. The hardware of this IC circuit design support apparatus is a computer system such as a work station.

15           The IC design support apparatus comprises a CPU 1, a ROM 2, a RAM 3, a memory 4, a hard disk drive (HDD) 5, a display 6, a keyboard 7, a mouse 8, and a printer 10.

          The CPU 1 controls the entirety of the apparatus.

          The ROM 2 stores control programs, etc.

          The RAM 3 temporarily stores data.

20           The memory 4 stores data mentioned below.

          The hard disk drive (HDD) 5 is a database to be reused for ASIC design, as will be described below in detail. The HDD 5 stores software tools, i.e. a simulation tool 5a, a logic synthesis tool 5b, a timing analysis tool 5c, a logic simulation tool 5d and a power consumption calculation tool 5e, which are  
25           executed by the CPU 1.

The display 6 displays various information.

The keyboard 7 and mouse 8 function as input devices.

5 The printer 10 performs a print-out operation as a printing apparatus.

10 As regards the above-described structure, the generation of a database and operations for information collection using the IC design support apparatus will now be described with reference to a flow chart of FIG. 2.

15 When a function design by RTL description made in a register transfer level has been carried out using HDL (VHDL, VERILOG) language, the CPU 1 of the IC design support apparatus executes simulation by means of the simulation tool 5a stored in the HDD 5 (ST1).

20 FIG. 3 shows an example of the function design by RTL description according to the present invention. The RTL description in this invention comprises a header portion and an entity portion. The RTL description is written in the HDD 5 as a reuse design database.

25 The CPU 1 generates a simulation result list (ST2). In this case, the list may be printed out by the printer 10 or displayed on the display 6.

FIG. 4 shows an example of a simulation result. In FIG. 4, "#799996" represents a simulation time.

The CPU 1 extracts the simulation time (step) from

the simulation result list and writes it in the header portion of the executed RTL description (ST3). The simulation time "#799996" nS shown in FIG. 4 is written in the header portion of the RTL description shown in FIG. 3.

Subsequently, the CPU 1 inputs the entity portion of the RTL description to the logic synthesis tool 5b and executes logic synthesis (ST4), and outputs a gate-level net list (ST5).

The CPU 1 inputs the net list to the timing analysis tool 5c and executes a timing analysis (ST6), and outputs an analysis report as an analysis result (ST7). In this case, the analysis report may be printed out by the printer 10 or displayed on the display 6.

FIGS. 5 and 6 show examples of the analysis report. FIG. 5 shows area information, and the total area is "31387.996094". FIG. 6 shows timing information, and the data arrival time is "-7.70".

The CPU 1 compares the values in the analysis report with pre-input desirable specifications (conditions for design) (ST8). If conditions for timing or layout area of the desirable specifications are not satisfied (area violation), the logic synthesis is executed once again (ST4).

If the conditions for timing and layout area of the desirable specifications are satisfied in step ST8,

the CPU 1 extracts the timing information and layout area information and writes the information in the header portion of the executed RTL description (ST9). The layout area information "31387.996094" gate in the area information shown in FIG. 5 and the timing information "-7.70" ns shown in FIG. 6 are written in the header portion of the RTL description shown in FIG. 3.

The CPU 1 executes a logic simulation for the gate-level net list by the logic simulation tool 5d (ST10). The CPU 1 then inputs the simulation data to the power consumption calculation tool 5d, carries out a power consumption calculation process (ST11) and outputs a power consumption calculation result list (power consumption data) (ST12). In this case, the list may be printed out by the printer 10 or displayed on the display 6.

FIG. 7 shows an example of the power consumption calculation result. In FIG. 7, PowerAVERAGE "5.00071" is a total power consumption.

The CPU 1 extracts power consumption information from the power consumption calculation result list and writes it in the header portion of the executed RTL description (ST13). The power consumption "5.00071" mA in FIG. 7 is written in the header portion of the RTL description in FIG. 3.

At last, the CPU 1 stores the RTL description



comprising the header portion and entity portion, as shown in FIG. 3, at a designated location of the HDD 5 as one file (ST14).

5 As has been described above, according to the embodiment, the processes of steps ST1-3, 4-9, 10-13 and 14 are automated. Thereby, the reuse design data comprises the header portion (information portion) and the RTL description portion (entity portion) and contains data in the same file. Thus, the reuse design  
10 database can easily be managed in a unified manner.

In the above embodiment, the four data items, i.e. simulation time, layout area, timing, and power consumption, are written in the information portion (header portion) of the database. Additionally, other  
15 necessary information may be written.

According to the above-described embodiment of the invention, there is no need to consume time in constructing a database after the completion of development of an ASIC, and efficient development can  
20 be made.

The management of the database can easily be made by unifying the information portion (header portion) and RTL description portion (entity portion) of the database in the same file.

25 Additional advantages and modifications will readily occur to those skilled in the art. Therefore, the invention in its broader aspects is not limited to

the specific details and representative embodiments  
shown and described herein. Accordingly, various  
modifications may be made without departing from the  
spirit or scope of the general inventive concept as  
defined by the appended claims and their equivalents.

5

100 101 102 103 104 105 106 107 108 109 110 111 112 113 114 115 116 117 118 119 120 121 122 123 124 125 126 127 128 129 130 131 132 133 134 135 136 137 138 139 140 141 142 143 144 145 146 147 148 149 150 151 152 153 154 155 156 157 158 159 160 161 162 163 164 165 166 167 168 169 170 171 172 173 174 175 176 177 178 179 180 181 182 183 184 185 186 187 188 189 190 191 192 193 194 195 196 197 198 199 200 201 202 203 204 205 206 207 208 209 210 211 212 213 214 215 216 217 218 219 220 221 222 223 224 225 226 227 228 229 230 231 232 233 234 235 236 237 238 239 240 241 242 243 244 245 246 247 248 249 250 251 252 253 254 255 256 257 258 259 260 261 262 263 264 265 266 267 268 269 270 271 272 273 274 275 276 277 278 279 280 281 282 283 284 285 286 287 288 289 290 291 292 293 294 295 296 297 298 299 300 301 302 303 304 305 306 307 308 309 310 311 312 313 314 315 316 317 318 319 320 321 322 323 324 325 326 327 328 329 330 331 332 333 334 335 336 337 338 339 340 341 342 343 344 345 346 347 348 349 350 351 352 353 354 355 356 357 358 359 360 361 362 363 364 365 366 367 368 369 370 371 372 373 374 375 376 377 378 379 380 381 382 383 384 385 386 387 388 389 390 391 392 393 394 395 396 397 398 399 400 401 402 403 404 405 406 407 408 409 410 411 412 413 414 415 416 417 418 419 420 421 422 423 424 425 426 427 428 429 430 431 432 433 434 435 436 437 438 439 440 441 442 443 444 445 446 447 448 449 450 451 452 453 454 455 456 457 458 459 460 461 462 463 464 465 466 467 468 469 470 471 472 473 474 475 476 477 478 479 480 481 482 483 484 485 486 487 488 489 490 491 492 493 494 495 496 497 498 499 500 501 502 503 504 505 506 507 508 509 510 511 512 513 514 515 516 517 518 519 520 521 522 523 524 525 526 527 528 529 530 531 532 533 534 535 536 537 538 539 540 541 542 543 544 545 546 547 548 549 550 551 552 553 554 555 556 557 558 559 560 561 562 563 564 565 566 567 568 569 570 571 572 573 574 575 576 577 578 579 580 581 582 583 584 585 586 587 588 589 590 591 592 593 594 595 596 597 598 599 600 601 602 603 604 605 606 607 608 609 610 611 612 613 614 615 616 617 618 619 620 621 622 623 624 625 626 627 628 629 630 631 632 633 634 635 636 637 638 639 640 641 642 643 644 645 646 647 648 649 650 651 652 653 654 655 656 657 658 659 660 661 662 663 664 665 666 667 668 669 670 671 672 673 674 675 676 677 678 679 680 681 682 683 684 685 686 687 688 689 690 691 692 693 694 695 696 697 698 699 700 701 702 703 704 705 706 707 708 709 710 711 712 713 714 715 716 717 718 719 720 721 722 723 724 725 726 727 728 729 730 731 732 733 734 735 736 737 738 739 740 741 742 743 744 745 746 747 748 749 750 751 752 753 754 755 756 757 758 759 760 761 762 763 764 765 766 767 768 769 770 771 772 773 774 775 776 777 778 779 780 781 782 783 784 785 786 787 788 789 790 791 792 793 794 795 796 797 798 799 800 801 802 803 804 805 806 807 808 809 810 811 812 813 814 815 816 817 818 819 820 821 822 823 824 825 826 827 828 829 830 831 832 833 834 835 836 837 838 839 840 841 842 843 844 845 846 847 848 849 850 851 852 853 854 855 856 857 858 859 860 861 862 863 864 865 866 867 868 869 870 871 872 873 874 875 876 877 878 879 880 881 882 883 884 885 886 887 888 889 890 891 892 893 894 895 896 897 898 899 900 901 902 903 904 905 906 907 908 909 910 911 912 913 914 915 916 917 918 919 920 921 922 923 924 925 926 927 928 929 930 931 932 933 934 935 936 937 938 939 940 941 942 943 944 945 946 947 948 949 950 951 952 953 954 955 956 957 958 959 960 961 962 963 964 965 966 967 968 969 970 971 972 973 974 975 976 977 978 979 980 981 982 983 984 985 986 987 988 989 990 991 992 993 994 995 996 997 998 999 1000